



Glavno

| | |
|---------------------------|------------------------------|
| Product name | Compact NS |
| Device short name | Compact NS800 NA |
| Product or component type | Switch disconnecter |
| Device application | Distribution |
| Offer type | C4 |
| Poles description | 4P |
| Network type | AC |
| Breaking capacity code | NA |
| Suitability for isolation | Yes according to IEC 60947-3 |

Komplementarno

| | |
|---|---|
| Network frequency | 50/60 Hz |
| Control type | Toggle |
| Mounting mode | Fixed |
| [Ie] rated operational current | AC-23A: 800 A AC 50/60 Hz 220/240 V AC-23A: 800 A AC 50/60 Hz 380/415 V AC-23A: 800 A AC 50/60 Hz 440/480 V AC-23A: 800 A AC 50/60 Hz 500/525 V AC-23A: 800 A AC 50/60 Hz 660/690 V |
| [Ui] rated insulation voltage | 800 V AC 50/60 Hz according to IEC 60947-3 |
| [Uimp] rated impulse withstand voltage | 8 kV according to IEC 60947-3 |
| [Ith] conventional free air thermal current | 800 A (60 °C) |
| [Icw] rated short-time withstand current | 25 kA (0.5 s) according to IEC 60947-3 4 kA (20 s) according to IEC 60947-3 |
| [Icm] rated short-circuit making capacity | 52 kA 690 V AC 50/60 Hz |
| [Ue] rated operational voltage | 690 V AC 50/60 Hz according to IEC 60947-3 |
| Contact position indicator | Yes |
| Visible break | No |
| Mechanical durability | 6000 cycles conforming to IEC 60947-3 |
| Electrical durability | 1000 cycles 440 V AC 50/60 Hz according to IEC 60947-3 |
| Connection pitch | 70 mm |
| Height | 327 mm |
| Width | 280 mm |
| Depth | 147 mm |
| Product weight | 18 kg |

Okolina

| | |
|---------------------------------------|----------------------------|
| standards | IEC 60947-3 |
| product certifications | ASEFA ASTA |
| pollution degree | 3 according to IEC 60947-3 |
| ambient air temperature for operation | -25...70 °C |
| ambient air temperature for storage | -50...85 °C |

Contractual warranty

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

