



## Glavno

Product name	Compact NS
Device short name	Compact NS630b NA
Product or component type	Switch disconnecter
Device application	Distribution
Offer type	C4
Poles description	3P
Network type	AC
Breaking capacity code	NA
Suitability for isolation	Yes according to IEC 60947-3

## Komplementarno

Network frequency	50/60 Hz
Control type	Motor mechanism
Mounting mode	Fixed
[Ie] rated operational current	AC-23A: 630 A AC 50/60 Hz 220/240 V AC-23A: 630 A AC 50/60 Hz 380/415 V AC-23A: 630 A AC 50/60 Hz 440/480 V AC-23A: 630 A AC 50/60 Hz 500/525 V AC-23A: 630 A AC 50/60 Hz 660/690 V
[Ui] rated insulation voltage	800 V AC 50/60 Hz according to IEC 60947-3
[Uimp] rated impulse withstand voltage	8 kV according to IEC 60947-3
[Ith] conventional free air thermal current	630 A ( 60 °C )
[Icw] rated short-time withstand current	25 kA ( 0.5 s ) according to IEC 60947-3 4 kA ( 20 s ) according to IEC 60947-3
[Icm] rated short-circuit making capacity	52 kA 690 V AC 50/60 Hz
[Ue] rated operational voltage	690 V AC 50/60 Hz according to IEC 60947-3
Contact position indicator	Yes
Visible break	No
Mechanical durability	6000 cycles conforming to IEC 60947-3
Electrical durability	1000 cycles 440 V AC 50/60 Hz according to IEC 60947-3
Connection pitch	70 mm
Height	327 mm
Width	210 mm
Depth	147 mm
Product weight	14 kg

## Okolina

standards	IEC 60947-3
product certifications	ASEFA ASTA
pollution degree	3 according to IEC 60947-3
ambient air temperature for operation	-25...70 °C
ambient air temperature for storage	-50...85 °C

## Contractual warranty

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.  
Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.  
Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.  
Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.

