



Glavno

| | |
|---------------------------|---------------------|
| Range of product | Sedna |
| Range | Sedna |
| Product or component type | Push-button |
| Switch function | 1-pole push-button |
| Device presentation | Without frame |
| Rated current | 10 A - 250 V AC |
| Cover plate colour tint | Aluminium |
| Marking | Bell symbol |
| Connections - terminals | Screwless terminals |

Komplementarno

| | |
|------------------------|---------------------------------------------------------------------|
| Power range | 2300 W |
| Wiring device mounting | Flush |
| Number of cables | 2 x 2.5 mm ² |
| Cable stiffness | Flexible Rigid |
| Wire stripping length | 13 mm |
| Material | Thermoplastic ABS-UV stabilised |
| Surface finish | Glossy |
| Fixing mode | Screws Screws Claws, span of claws working range : 51...70 mm |
| Height | 71 mm |
| Width | 71 mm |
| Depth | 37 mm |
| Projecting depth | 12 mm |
| Product weight | 0.07064 kg |

Okolina

| | |
|-------------------------|-------------|
| standards | IEC 60669-1 |
| quality labels | CE |
| product certifications | GOST-R |
| IP degree of protection | IP20 |

Offer Sustainability

| | |
|-----------------------------------------------------------------------|-----------------------------------------------------------------------|
| Green Premium product | Green Premium product |
| Compliant - since 1715 - Schneider Electric declaration of conformity | Compliant - since 1715 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Need no specific recycling operations | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.
 Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.
 Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.
 Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.