



Glavno

| | |
|---------------------------|--------------------|
| Range of product | Cedar Plus |
| Product or component type | Switch |
| Switch function | 1-pole 2-circuit |
| Device presentation | Complete product |
| Pilot light | Without pilot lamp |
| Cover plate colour tint | White |

Komplementarno

| | |
|-------------------------|-----------------------|
| Wiring device mounting | Surface |
| Power range | 3680 W |
| Rated current | 16 AX 250 V AC |
| Connections - terminals | Lift terminals |
| Number of cables | 2 2.5 mm ² |
| Cable stiffness | Flexible Rigid |
| Wire stripping length | 11 mm |
| Material | PA6 FR850 |
| Surface finish | Glossy |
| Height | 79 mm |
| Width | 66 mm |
| Depth | 48 mm |
| Product weight | 0.098 kg |

Okolina

| | |
|-------------------------|------|
| product certifications | CE |
| IP degree of protection | IP44 |

Offer Sustainability

| | |
|---|---|
| Green Premium product | Green Premium product |
| Compliant - since 0826 - Schneider Electric declaration of conformity | Compliant - since 0826 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Need no specific recycling operations | Need no specific recycling operations |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.
 Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.
 Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poipunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.
 Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu sadržanih informacija.