


## Podatkovni list proizvoda

### Karakteristike

## GV7AS207

TeSys GV7 – oslobađanje napona – 200...240 V AC  
50/60 Hz



### Glavno

Range	TeSys
Product or component type	Shunt trip
Device short name	GV7AS
Device application	Control
Range compatibility	TeSys TeSys GV7

### Komplementarno

[Uc] control circuit voltage	200...240 V AC 50/60 Hz
Control circuit voltage limits	0.7...1.1 Un
[Ui] rated insulation voltage	600 V AC conforming to UL 508 control circuit 690 V AC conforming to IEC 60947-1 control circuit 600 V AC conforming to CSA C22.2 No 14 control circuit
Threshold tripping voltage	0.2...0.75 Ue
Inrush power in VA	< 10 VA for AC network
Hold-in power consumption in VA	< 5 VA for AC network
Operating time	< 50 ms conforming to IEC 60947-1
On-load factor	100 %
Connections - terminals	Control circuit: screw clamp terminals 1 cable 1 mm <sup>2</sup> - cable stiffness: flexible - with cable end Control circuit: screw clamp terminals 1 cable 1.5 mm <sup>2</sup> - cable stiffness: flexible - without cable end Control circuit: screw clamp terminals 1 cable 1.5 mm <sup>2</sup> - cable stiffness: solid
Tightening torque	Control circuit: 1.2 N.m - on screw clamp terminals
Product weight	0.105 kg
Quantity per set	Set of 10

### Okolina

#### Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 0744 - Schneider Electric declaration of conformity	Compliant - since 0744 - Schneider Electric declaration of conformity

#### Contractual warranty

Warranty period	18 months
-----------------	-----------

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i potpunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric, Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.