



### Glavno

Range	Prisma
Range compatibility	Prisma G Pack 160
Product or component type	Rail
Accessory / separate part category	Installation accessory
Type of rail	Modular Rear
Installed device	Altistart: ATS01N

### Komplementarno

Enclosure/cubicle description	Floor-standing enclosure - width 600 mm Wall-mounted enclosure - width 600 mm Pack enclosure - width 555 mm
Number of vertical modules [50 mm]	5 module(s) : ATS01N in 600 mm Wide floor-standing enclosure 5 module(s) : ATS01N in 600 mm Wide wall-mounted enclosure 6 module(s) : ATS01N in 600 mm Wide floor-standing enclosure 6 module(s) : ATS01N in 600 mm Wide wall-mounted enclosure 5 module(s) : ATS01N in 555 mm Wide Pack enclosure 6 module(s) : ATS01N in 555 mm Wide Pack enclosure
9 mm pitches	48
Quantity per set	Set of 1
Height	35 mm
Width	464 mm
Depth	36 mm
Product weight	0.18 kg
Colour	Grey
Material	Metal

### Okolina

standards	IEC 61439-2 IEC 61439-1
product certifications	ASEFA

### Offer Sustainability

Green Premium product	Green Premium product
Compliant - since 0807 - Schneider Electric declaration of conformity	Compliant - since 0807 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold
Available	Available
Need no specific recycling operations	Need no specific recycling operations

### Contractual warranty

Warranty period	18 months
-----------------	-----------

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda.  
Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene.  
Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog.  
Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.