



Glavno

| | |
|------------------------------|----------------------------------|
| Range | TeSys |
| Product or component type | Coil |
| Range compatibility | TeSys Integral contactor breaker |
| Product compatibility | LD.LD...BD |
| Device short name | LX1 |
| Control circuit type | AC 50 Hz |
| [Uc] control circuit voltage | 24 V AC 50 Hz |
| Average resistance | 0.323 Ohm at 20 °C |
| Inductance of closed circuit | 0.071 H |

Komplementarno

| | |
|---------------------------------|---|
| Control circuit voltage limits | 0.85...1.1 Uc at <= 55 °C operational 0.25...0.7 Uc at <= 55 °C drop-out |
| Inrush power in VA | 350...400 VA (cos φ 0.55) 50 Hz |
| Hold-in power consumption in VA | 20...30 VA (cos φ 0.28) 50 Hz |

Okolina

| | |
|----------------|--------|
| product weight | 0.3 kg |
|----------------|--------|

Offer Sustainability

| | |
|---|---|
| Green Premium product | Green Premium product |
| Compliant - since 0808 - Schneider Electric declaration of conformity | Compliant - since 0808 - Schneider Electric declaration of conformity |
| Reference not containing SVHC above the threshold | Reference not containing SVHC above the threshold |
| Available | Available |
| Available | Available |

Contractual warranty

| | |
|-----------------|-----------|
| Warranty period | 18 months |
|-----------------|-----------|

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.