



### Glavno

Range of product	Harmony XAR
Accessory / separate part type	Battery charger
Accessory / separate part category	Electrical accessory

### Komplementarno

[Us] rated supply voltage	100...240 V AC
Network frequency	50...60 Hz
Nominal output current	0.9 A at 90 V AC
Connections - terminals	5-position plug-in connector
Product weight	0.26 kg

### Okolina

ambient air temperature for operation	> 0...40 °C
ambient air temperature for storage	> -20...60 °C

### Offer Sustainability

Not Green Premium product	Not Green Premium product
Compliant - since 1415 - Schneider Electric declaration of conformity	Compliant - since 1415 - Schneider Electric declaration of conformity
Reference not containing SVHC above the threshold	Reference not containing SVHC above the threshold

Informacije dane u ovoj dokumentaciji sadrže opće opise i/ili tehničke karakteristike o performansama ovdje sadržanih proizvoda. Ova dokumentacija nije namijenjena kao zamjena za niti bi se trebala koristiti za određivanje prikladnosti ili pouzdanosti predmetnih proizvoda za konkretne korisničke primjene. Svaki takav korisnik ili integrator dužan je provesti odgovarajuću i poplunu analizu rizika, procjenu i ispitivanje proizvoda u odnosu na odgovarajuću specifičnu primjenu ili uporabu istog. Niti društvo Schneider Electric Industries SAS niti bilo koje od njegovih povezanih poduzeća ili podružnica neće preuzeti obvezu ili snositi odgovornost za pogrešnu upotrebu ovdje sadržanih informacija.